

WORKING GROUP REPORT

Compliance Working Group (Technical Performance)

**Prepared by the Compliance Working Group
for submission to the Grid Code Review Panel**

Reference	Compliance WG Report (Technical Performance)
Issue	0.1
Date of Issue	April 2008
Prepared by	Compliance WG

I DOCUMENT CONTROL

a National Grid Document Control

Version	Date	Author	Change Reference
0.1	15/04/2008	M Horley	Draft for Comment by Working Group Members
1.0	30/04/2008	M Horley	Final WG Report

b Distribution

Name	Organisation
GCRP Members	GCRP

II	CONTENTS TABLE	
1.0	INTRODUCTION	4
2.0	BACKGROUND	4
3.0	GLOSSARY AND DEFINITIONS	4
4.0	PLANNING CODE	4
5.0	POWER SYSTEM STABILISER	5
6.0	OPERATION ABOVE 50.5Hz	6
7.0	WORKING GROUP RECOMMENDATIONS	6
8.0	IMPACT ON GRID CODE	6
9.0	IMPACT ON INDUSTRY DOCUMENTS	6
10.0	IMPACT ON GB TRANSMISSION SYSTEM	6
11.0	IMPACT ON GRID CODE USERS	7
12.0	ASSESSMENT AGAINST APPLICABLE CODE OBJECTIVES	7
	ANNEX 1 – WORKING GROUP TERMS OF REFERENCE	8
	ANNEX 2 – PROPOSED GRID CODE CHANGES	10

1.0 INTRODUCTION

- 1.1 This paper outlines the technical performances expected of generating plant that have been assumed as part of the compliance process which should be properly included within the Grid Code to allow industry scrutiny.

2.0 BACKGROUND

- 2.1 The industry, through the GCRP expressed concern that National Grid was applying generating unit performance criteria and test requirements in Compliance Guidance that was not being explicitly called for in the Grid Code or CUSC / Bilateral Connection Agreements. To address this concern National Grid has formed a Grid Code Working Group to look at the whole "Compliance Issue" including the process, the relationship with OC5 and the technical performance requirements.
- 2.2 This report contains the technical plant issues that National Grid expected to be met and which were highlighted in the Compliance Guidance but are not currently explicitly in the Grid Code. The Grid Code changes proposed below have come to light following the publication of the G/06 consultation and the release of greatly enhanced draft guidance documents to compliment.
- 2.3 The proposals were discussed at the Compliance Working Group meetings on 15 January 2008 and 8 April 2008. Subsequently, National Grid has modified the wording in the code drafting and in this paper to respond to comments received.
- 2.4 The proposed changes relating to the specification of the Power System Stabiliser were drafted against the words included in the G/06 consultation. G/06 was subsequently approved for implementation by Ofgem with effect from 1st April 2008. The remaining proposals relate to text in the Grid Code prior to the G/06 Report and are unaffected by the G/06 Report.

3.0 GLOSSARY AND DEFINITIONS

- 3.1 The consultation G/06 included a change to CC.6.3.7 (c)(ii) to improve the interpretation of droop in wind farms. National Grid proposed a similar change to the Droop definition in the Glossary & Definitions section of the Grid Code. However, the Working Group considered that clarity would be enhanced by simplification of the Droop definition removing references to plant types. This is shown in Annex 2 of this paper.

4.0 PLANNING CODE

- 4.1 The Planning Code requires the submission of control system models for both synchronous and non-synchronous generation to allow National Grid to simulate system behavior to ensure stable operation. Obviously the control system models should represent the behavior of the real generation plant. While the changes made by H/04 partially addressed the need for the models to be validated for Power Park Modules, the drafting was not as explicit as it could have been and the requirement was not extended to traditional synchronous generation.
- 4.2 The working group were concerned that this should not be retrospectively applied to existing control systems on synchronous generating units subject to routine

maintenance. National Grid agrees where routine refurbishment of components does not change the control system performance then there is no requirement to update the data but, believes that when Generators are investing in replacing control system, the performance of the revised transfer block diagram should initially be verified by the user. The Planning Code drafting proposed in Annex 2 includes implementation dates and only applies to control system replacement where there is a change in data items.

- 4.3 The validation of the transfer block diagram as a representation of the synchronous generator performance can only be validated at the end of commissioning and testing as part of the compliance process. This validation will be discussed as part of the compliance process drafting currently being developed by the Working Group.

5.0 POWER SYSTEM STABILISER

- 5.1 The changes consulted on under G/06 transferred the majority of the requirements for excitation systems from Bilateral Agreements into the Grid Code. The compliance process guidance notes had additional clarifications on excitation systems that it is now proposed to include in the Grid Code.
- 5.2 It has been noted that the wording limiting the magnitude of the Power System Stabiliser output could be misconstrued, so a minor change to CC.A.6.2.5.4 is proposed.
- 5.3 The wording of BC2.11.2 states that the Power System Stabiliser should be left in service once commissioned. However it might be construed that the Power System Stabiliser may be automatically disabled by the functions within the excitation system such as the Under Excitation Limiter. While these limiter functions may curtail the excitation system output, the Power System Stabiliser and Automatic Voltage Regulator should still be active.
- 5.4 There is also the potential for confusion when a Generating Unit is operating as a motor as in a Pumped Storage Power Station. National Grid would like to clarify this by adding to the text introduced by G/06 for CC.A.6.2.5.8.
- 5.5 With modern governor systems some Generating Units, notably Pumped Storage are able to execute very fast changes in mechanical power. A Power System Stabiliser may try to counteract this mechanical power change by altering the excitation phasing producing large swings in reactive output. This is undesirable for stable voltage control and it is therefore proposed to include an additional clause in CC.A.6.2.5.3.
- 5.6 Draft wording for these Power System Stabiliser issues can be found in Annex 2 and is based on the wording introduced to the Connection Conditions by the G/06 Report to Ofgem. The conditions of CC.A.6 are subject to an implementation date to avoid creating issues with existing plant and excitation systems. Therefore National Grid does not believe that these proposals will impact on existing users.

6.0 OPERATION ABOVE 50.Hz

- 6.1 For Frequency Sensitive Mode (FSM), generating units are required to provide

response in accordance with the frequency response matrix values agreed in the Mandatory Services Agreement. The High Frequency Response level in the agreement is limited to 50.5Hz. However, if the frequency continues to rise above 50.5 Hz, BC3.7.1(c) requires stations to continue to reduce their output.

- 6.2 This continual reduction capability is critical to system security as the system frequency at this time would already be above its statutory limit indicating the system is already under stress. It is imperative that all generating stations including those not in frequency sensitive mode are required to reduce output to contain the system frequency rise. This condition if not controlled could lead to the frequency being driven above 52 Hz and the collapse of the system.
- 6.3 National Grid believes that the requirement in BC3.7.1(c) should be improved by incorporating a more detailed breakdown of the power reduction process as that adopted in BC3.7.2 for the Limited Frequency Sensitive Mode (LFSM) operation. The overall timescales allowed for the reduction in power remain unchanged and therefore, in National Grids opinion, have no impact on existing generation. However, following comments received, the more detailed wording was amended to explicitly exclude existing power stations. A draft showing how BC.3.7.1(c) would look is included in Annex 2.

7.0 RECOMMENDATIONS OF THE WORKING GROUP

- 7.1 The Grid Code Review Panel is asked to consider the drafting proposed by the Compliance Working Group and agree that National Grid should proceed with a formal consultation. National Grid agrees with the recommendations of the Working Group.

8.0 IMPACT ON GRID CODE

- 8.1 The proposed changes require amendments to the following Grid Code sections:
- i. Glossary and Definitions
 - ii. Planning Code
 - iii. Connections Code
 - iv. Balancing Code
- 8.2 The associated legal text for the Working Group recommendations is outlined in Annex 2.

9.0 IMPACT ON INDUSTRY DOCUMENTS

Impact on Core Industry Documents

- 9.1 None.

Impact on other Industry Documents

- 9.2 None.

10.0 IMPACT ON GB TRANSMISSION SYSTEM

10.1 The Working Groups' preferred solution will have no material impact on the GB Transmission System.

11.0 IMPACT ON GRID CODE USERS

11.1 The Working Groups' preferred solution will provide a high level of transparency within the Grid Code of the Technical Performance requirements associated with the Compliance process.

12.0 ASSESSMENT AGAINST GRID CODE OBJECTIVES

12.1 The proposed changes outlined in the Working Group would better facilitate Grid Code Objectives:

ii) to facilitate competition in the generation and supply of electricity

by reassuring Users that the Technical Performance Guidelines have been appropriately codified in the Grid Code

ANNEX 1 – WORKING GROUP TERMS OF REFERENCE

Grid Code Compliance Working Group

Terms of Reference

Objective

At September 2007 GCRP it was agreed to establish a Grid Code Working Group which would be tasked with the review and recommendation of the codification of the compliance process and technical performance obligations (currently specified in the Compliance Guidance Notes).

Scope of Work

The group will address the following issues, as agreed by the GCRP:

- (a) Technical Performance
The Working Group to review, identify and resolve any disparity between the Grid Code and Compliance Guidance Notes regarding technical performance obligations.
- (b) Compliance Process
The Working Group will consider and make applicable recommendations regarding the codification of the compliance process (commissioning and lifetime phase) for directly connected and Large Power Stations into the Grid Code.
- (c) OC5 Review
The Working Group will consider the applicability of the current OC5 provisions in light of the possible codification of the compliance process.
- (d) Review of LEEMPS
The Working Group will re-evaluate the existing Licence Exempt Embedded Medium Power Stations provisions with particular reference to the respective responsibilities of Users and NGET and identify applicable recommendations.

Deliverables

National Grid will produce:

- a GCRP paper recommending a way forward on the above issues, reflective of the group discussions and identification of consequential changes which may be required to other industry codes
- draft legal text of any proposed Grid Code changes

Approach

Given the remit of the Working Group which is definable by distinct work areas, it is recommended that the findings are represented to the GCRP via the individual workstreams:

1. Technical Performance
A separate Working Group Report will be presented to the GCRP and an individual Consultation Report will be issued.
2. Compliance Process and Review of OC5
A separate Working Group Report will be presented to the GCRP and an individual Consultation Report will be issued. Depending on the interactivity between the compliance process and review of OC5, it may be appropriate to split the proposals into separate Working Group/Consultation Reports.

Timescales

The Working Group will aim to report back its recommendations from all workstreams by the February 2009 GCRP meeting. The GCRP will receive regular updates on the progress of the Working Group. It is anticipated that the Technical Performance recommendations will be presented to the May 2008 GCRP.

Membership

The membership of the working group will be drawn from the GCRP or their nominated representatives, the Relevant Transmission Licensees, and Ofgem.

Compliance Working Group Members

Members of the GCRP Working group will be as follows:

Chair

Mark Perry

National Grid

Secretary

Richard Dunn

National Grid

National Grid Representatives

Mark Horley

Helge Urdal

Steve Hoar

Kathryn Sorrell

Industry Representatives

Chris Berry

Scottish Power Networks

Claire Maxim

E.ON

John Norbury

RWE Trading

Mick Chowns

RWE Trading

Damien McCool

Scottish Power Renewables

Mike Kay

Electricity North West

John Morris

British Energy

Authority Observer

Bridget Morgan

Ofgem

ANNEX 2 – PROPOSED GRID CODE CHANGES

Droop definition clarification (Glossary and Definitions)

Droop The ratio of the per unit steady state change in speed, or in **Frequency** in the case of a ~~Generating Unit~~, or in **Frequency** in the case of a **Power Park**, to the per unit steady state change in power output of the ~~Generating Unit or Power Park~~.

Planning Code

- PC.A.5.3.2
(c) Excitation Control System parameters

Note: The data items requested under Option 1 below may continue to be provided in relation to **Generating Units** on the **System** at 09 January 1995 (in this paragraph, the "relevant date") or the new data items set out under Option 2 may be provided. **Generators** or **Network Operators**, as the case may be, must supply the data as set out under Option 2 (and not those under Option 1) for **Generating Unit** excitation control systems commissioned after the relevant date, those **Generating Unit** excitation control systems recommissioned for any reason such as refurbishment after the relevant date and **Generating Unit** excitation control systems where, as a result of testing or other process, the **Generator** or **Network Operator**, as the case may be, is aware of the data items listed under Option 2 in relation to that **Generating Unit**. In addition, where refurbishment results in revision of data items submitted under Option 2 after 1 January 2009, the excitation system block diagrams should have been verified as far as reasonably practicable through simulation studies and this shall be confirmed by the Generator.

-
(d) Governor Parameters

Incremental Droop values (in %) are required for each **Generating Unit** at six MW loading points (MLP1 to MLP6) as detailed in PC.A.5.5.1 (this data item needs only be provided for **Large Power Stations**)

Note: The data items requested under Option 1 below may continue to be provided by **Generators** in relation to **Generating Units** on the **System** at 09 January 1995 (in this paragraph, the "relevant date") or they may provide the new data items set out under Option 2. **Generators** must supply the data as set out under Option 2 (and not those under Option 1) for **Generating Unit** governor control systems commissioned after the relevant date, those **Generating Unit** governor control systems recommissioned for any reason such as refurbishment after the relevant date and **Generating Unit** governor control systems where,

as a result of testing or other process, the **Generator** is aware of the data items listed under Option 2 in relation to that **Generating Unit**. In addition, where a refurbishment results in revision of data items submitted under Option 2 after 1 January 2009, the governor system block diagram should have been verified as far as reasonably practicable through simulation studies and this shall be confirmed by the Generator.

PC.A.5.4.2 The following **Power Park Unit**, **Power Park Module** and **Power Station** data should be supplied in the case of a **Power Park Module** not connected to the **Total System** by a **DC Converter**:

(a) **Power Park Unit** model

A mathematical model of each type of **Power Park Unit** capable of representing its transient and dynamic behavior under both small and large disturbance conditions. The model shall include non-linear effects and represent all equipment relevant to the dynamic performance of the **Power Park Unit** as agreed with **NGET**. The model shall be suitable for the study of balanced, root mean square, positive phase sequence time-domain behaviour, excluding the effects of electromagnetic transients, harmonic and sub-harmonic frequencies.

The model shall accurately represent the overall performance of the **Power Park Unit** over its entire operating range including that which is inherent to the **Power Park Unit** and that which is achieved by use of supplementary control systems providing either continuous or stepwise control. Model resolution should be sufficient to accurately represent **Power Park Unit** behavior both in response to operation of transmission system protection and in the context of longer-term simulations.

The overall structure of the model shall include:

- (i) any supplementary control signal modules not covered by (c), (d) and (e) below.
- (ii) any blocking, deblocking and protective trip features that are part of the **Power Park Unit** (e.g. "crowbar").
- (iii) any other information required to model the **Power Park Unit** behaviour to meet the model functional requirement described above.

The model shall be submitted in the form of a transfer function block diagram and may be accompanied by dynamic and algebraic equations.

This model shall display all the transfer functions and their parameter values, any non wind-up logic, signal limits and non-linearities.

The submitted **Power Park Unit** model and the supplementary control signal module models covered by (c),(d) and (e) below shall have been validated and this shall be confirmed by the **Generator**. The validation shall be based on comparing the submitted model simulation results against measured test results. Validation evidence shall also be submitted and this shall include the simulation and measured test results. The latter shall include appropriate short-circuit tests. In the case of an **Embedded Medium Power Station** not subject to a **Bilateral Agreement** the **Network Operator** will provide **NGET** with the validation evidence if requested by **NGET**. The validation of the supplementary control signal module models covered by (c), (d) and (e) below applies only to a Power Station with a completion date after 1 January 2009.

(b) **Power Park Unit** parameters

.....

Connection Conditions

CC.A.6.2.5.3 The arrangements for the supplementary control signal shall ensure that the **Power System Stabiliser** output signal relates only to changes in the supplementary control signal and not the steady state level of the signal. For example, if generator electrical power output is chosen as a supplementary control signal then the **Power System Stabiliser** output should relate only to changes in generator electrical power output and not the steady state level of power output. Additionally the Power System Stabiliser should not react to mechanical power changes in isolation for example during changes in steady state load or when providing frequency response.

CC.A.6.2.5.4 The output signal from the **Power System Stabiliser** shall be limited to not more than $\pm 10\%$ of the **Generating Unit** terminal voltage signal at the **Automatic Voltage Regulator** input. The gain of the **Power System Stabiliser** shall be such that an increase in the gain by a factor of 3 shall not cause instability.

.....

CC.A.6.2.5.6 The **Generator** will agree **Power System Stabiliser** settings with **NETG** prior to the on-load commissioning detailed in BC2.11.2(d). To allow assessment of the performance before on-load commissioning the **Generator** will provide to **NETG** a report containing:

- i. the **Excitation System** model including the **Power System Stabiliser** with settings as required under the **Planning Code** (PC.A.5.3.2(c)).
- ii. on load time series simulations of the response of the **Excitation System** with and without the **Power System Stabiliser** to 2% and 10% steps in the reference voltage and a three phase short circuit fault applied to the higher voltage side of the **Generating Unit** transformer for 100 ms. The results should show field voltage, **Generating Unit** terminal voltage, **Power System Stabiliser** output and **Generating Unit Active Power** and **Reactive Power** output.
- iii. gain and phase Bode diagrams for the open loop frequency domain response of the **Generating Unit Excitation System** with and without the **Power System Stabiliser**, operating under maximum leading conditions and minimum fault level conditions as agreed with **NETG**. These should be in a format to allow assessment of the phase contribution of the **Power System Stabiliser** and the gain and phase margin of the **Excitation System** with the **Power System Stabiliser**

CC.A.6.2.5.7 The Power System Stabiliser must be active within the Excitation System at all times when synchronised including when the Under Excitation Limiter or Over-Excitation Limiter are active. When operating at low load when Synchronising or De-Synchronising a Generating Unit the Power System Stabiliser may be out of service.

CC.A.6.2.5.8 Where a **Power System Stabiliser** is fitted to a **Pumped Storage Unit** it must function when the **Pumped Storage Unit** is in both generating and pumping modes.

Balancing Code 3

BC3.7.1 Plant in Frequency Sensitive Mode instructed to provide High Frequency Response

- (c) In addition to the High Frequency Response provided, the Genset (or DC Converter at a DC Converter Station) must continue to reduce Active Power output in response to an increase in System Frequency ~~up to~~ above 50.5 Hz ~~or above~~ at a minimum rate of 2 per cent of output per 0.1 Hz deviation of System Frequency above that level, such reduction to be achieved within five minutes of the rise to or above 50.5 Hz. For a Power Station with a Completion Date after 1st January 2009 this reduction in Active Power should be delivered in accordance with in (i) to (iv) below. For the avoidance of doubt, the provision of this reduction in Active Power output is not an Ancillary Service.
- (i) The reduction in Active Power output must be continuously and linearly proportional as far as practical, to the excess of Frequency above 50.5 Hz and must be provided increasingly with time over the period specified in (iii) below.
- (ii) As much as possible of the proportional reduction in Active Power output must result from the frequency control device (or speed governor) action and must be achieved within 10 seconds of the time of the Frequency increase above 50.5 Hz.
- (iii) The residue of the proportional reduction in Active Power output which results from automatic action of the Genset (or DC Converter at a DC Converter Station) output control devices other than the frequency control devices (or speed governors) must be achieved within 3 minutes from the time of the Frequency increase above 50.5 Hz.
- (iv) Any further residue of the proportional reduction which results from non-automatic action initiated by the Generator or DC Converter Station owner shall be initiated within 2 minutes, and achieved within 5 minutes, of the time of the Frequency increase above 50.5 Hz.